

Copyright is owned by the Author of the thesis. Permission is given for a copy to be downloaded by an individual for the purpose of research and private study only. The thesis may not be reproduced elsewhere without the permission of the Author.

Motor Control of a Hub Motor for Electric Skateboard Propulsion

A thesis presented in partial fulfilment
of the requirements for the degree of

Masters
in
Engineering

at
Massey University
Palmerston North
New Zealand

Alex Rowe
2016



Abstract

An electric powered skateboard was designed and built for testing and development of an innovative hub motor propulsion system and motor controller. The electric skateboard prototype is able to reach speeds of over 50km/h and achieve a range of over 35km on a single battery charge. The prototype weighs 8.6kg and can easily be carried by the user. This mode of transport has potential uses in recreational use, motor sports (racing), short commutes, and most notably, in 'the last mile' of public transport – getting to and from a train station, bus stop, etc. to the user's final destination.

Typical electric powered skateboards use external motors(s) requiring a power transmission assembly to drive the wheels. The hub motor design places the motor(s) inside the skateboard wheels and drives the wheels directly. This removes the need for power transmission assemblies therefore reductions in size, weight, cost, audible noise, and maintenance are realised. The hub motor built for this prototype has proven to be a highly feasible option over typical drive systems and further improvements to the design are discussed in this report.

Advances in the processor capability of low cost microcontrollers has allowed for advanced motor control techniques to be implemented on low cost consumer level motor controllers which, until recent times, have been using the basic 'Six-Step Control' technique to drive Permanent Magnet Synchronous Motors. The custom built motor controllers allow for firmware to be flashed to the microcontroller. Firmware was written for the basic motor control technique, Six-Step Control and for the advanced motor control technique, 'Field Oriented Control' (FOC). This allowed for the two control techniques to be tested and compared using identical hardware for each.

Six-Step Control drives a three phase motor by controlling the inverter output to six discrete states. The states are stepped through sequentially. This results in a square wave AC waveform. Theory shows that this is not optimal as the magnetic flux produced in the stator is not always perpendicular to the magnet poles but rather aligned to the nearest 60° . FOC addresses this by controlling the magnetic flux to always be perpendicular to the magnet poles in order to maximise torque. The inverter is essentially controlled to produce a continuously variable voltage vector output in terms of both magnitude and direction (vector control).

Bench testing of the control techniques was performed using two motors coupled together with one motor driving and the other motor running as a generator. The generator motor was shown to provide a highly consistent and repeatable load on the driving motor under test and therefore comparisons could be made between the performance of the motor while controlled under Six-Step Control and FOC. This test indicated that FOC was able to drive the motor more efficiently than Six-Step Control, however the FOC implementation requires further development to achieve greater efficiency under high load demands. Furthermore, on-road testing was performed using the motor controllers in the electric skateboard prototype to compare the performance of the two control techniques in a real world application. The results from this test were inconclusive due to large variation in the results between repeated tests.

Acknowledgements

In completing this Masters of Engineering degree in Mechatronics, I would like to take this opportunity to sincerely thank:

My Supervisor, Dr Gourab Sen Gupta from the School of Engineering and Advanced Technology (SEAT), Massey University, Palmerston North, New Zealand for his patience and guidance throughout this project.

Mr Clive Bardell and Mr Kerry Griffiths from Massey University's SEAT workshop and CNC lab for their guidance and expertise in teaching me the skills required to fabricate various parts for the project.

Mr Dennis Rowe, Project Manager at Winstone Pulp International, Karioi, Ohakune, New Zealand for the use of equipment and guidance in building the hub motor prototype.

Table of Contents

1.	Introduction	1
1.1.	Modern Electric Vehicles	1
1.2.	Basic Principles.....	2
1.2.1.	Batteries.....	2
1.2.2.	Motor Controller.....	4
1.2.3.	Motor	6
1.3.	Design Objectives.....	9
2.	Basic Principles for Electric Motor Analysis	10
2.1.	Electromagnetic Theory	10
2.1.1.	Magnetic Field, B	10
2.1.2.	Permeability, μ	10
2.1.3.	Magnetic Circuits	11
2.1.4.	Magnetic Flux, Φ_B	12
2.1.5.	Flux Linkage, λ	12
2.1.6.	Lorentz Force	13
2.1.7.	Faraday's Law of Induction	13
2.2.	Electric Motor Theory	13
2.2.1.	Motor Constant.....	14
2.2.2.	Electric Motor Model	16
2.2.3.	Saliency	18
2.2.4.	Motor Equations	19
2.2.5.	Power Losses.....	21
2.2.6.	Outer Rotor Motor	24
2.3.	Motor Control Theory	25
2.3.1.	Motor Control Techniques.....	25
2.3.2.	Reference Frames	25
2.3.3.	Six Step Control.....	30
2.3.4.	Field Oriented Control	35
2.3.5.	Comparison of Six-Step Control and FOC.....	38
3.	Prototype Design	39

3.1.	Design Considerations.....	39
3.1.1.	Motor Controller.....	40
3.1.2.	Turning Radius	40
3.1.3.	Size and Weight.....	41
3.1.4.	Hub Motor Design.....	41
3.1.5.	Physical Layout of Equipment	42
3.1.6.	Handheld Controller.....	42
3.2.	Power Requirement Modelling.....	43
3.2.1.	Model Formulae.....	43
3.2.2.	Matlab Model.....	47
3.3.	Equipment Selection	48
3.3.1.	Motors and Wheels.....	49
3.3.2.	Battery Selection.....	51
3.3.3.	Motor Controller	53
3.4.	Building the Hub Motor	55
3.4.1.	Stator Assembly	55
3.4.2.	Rotor Assembly	57
3.4.3.	Hall Sensors.....	58
3.4.4.	Temperature Sensors.....	59
3.4.5.	Rust Protection	59
3.4.6.	Hub Motor Assembly.	60
3.5.	Electronics Enclosure	61
3.5.1.	Equipment Layout.....	61
3.5.2.	Fibreglass Enclosure.....	61
3.6.	Complete Electric Skateboard Prototype.....	62
4.	Custom Built Motor Controllers.....	63
4.1.	Hardware.....	63
4.1.1.	Microcontroller	63
4.1.2.	Switching Device	64
4.1.3.	Gate Driver	65
4.1.4.	Current Sensing.....	66
4.1.5.	Power Supplies.....	66

4.1.6.	DC Bus Capacitors	66
4.1.7.	Heat Sink	69
4.1.8.	Hall Sensor Interface	69
4.1.9.	Throttle Input	70
4.1.10.	Analogue Debug Outputs	70
4.1.11.	Communication Ports	70
4.1.12.	Component Layout.....	71
4.1.13.	Complete Motor Controller Hardware	74
4.2.	Software	74
4.2.1.	Six-Step Control.....	75
4.2.2.	FOC.....	80
5.	Results.....	83
5.1.	Bench Testing.....	83
5.1.1.	Test Rig.....	83
5.1.2.	Test Setup	86
5.1.3.	Test Results	86
5.1.4.	Bench Testing Conclusions.....	89
5.2.	On-road Testing	92
5.2.1.	Test Rig.....	93
5.2.2.	Test Setup	93
5.2.3.	Test Results	94
5.2.4.	On Road Testing Conclusions.....	99
6.	Improvements.....	101
6.1.	Hub Motor Improvements	101
6.1.1.	Larger Bearings.....	101
6.1.2.	Skateboard Wheel Mechanical Fixing.....	101
6.1.3.	Custom Wound Stator	101
6.2.	Motor Controller	102
6.2.1.	Miniaturisation.....	102
6.2.2.	Current Sensing Improvements	102
6.2.3.	Fast Over-current Protection	102
6.3.	General Improvements	103

6.3.1.	Battery Isolator	103
6.3.2.	Weight Reduction	103
6.3.3.	Water Resistance	104
7.	Concluding Remarks.....	105
7.1.	Complete Prototype.....	105
7.2.	Hub Motor.....	105
7.3.	Motor Controller	106
7.4.	Motor Control Techniques.....	106
8.	References	108
9.	Appendices.....	112
	Appendix A - Journal Article Published in IEEE International Instrumentation and Measurement Technology Conference (I2MTC 2012)	112
	Appendix B - Matlab Script for Simulation of the Electric Skateboard Prototype Performance....	119
	Appendix C - Altium Designer Printouts of the Motor Controller PCB Design	123
	Appendix D- Motor Controller Firmware Source Code.....	134
	Appendix E- Bench Testing Minitab Data Analysis	156
	Appendix F - On-road Testing Data Analysis.....	180

List of Figures

Figure 1.1 - Bar graph showing specific energy densities of common battery chemistries. Lead-acid batteries are shown in red colour, Nickel based batteries in green, and Lithium based batteries in orange. (Buchmann, 2015)..... 3

Figure 1.2 - Three Phase H-Bridge showing flow of current with phase A-High and phase B-Low switches in the 'on' state..... 5

Figure 1.3 - Electric motor classification (Natural Resources Canada, 2014). 7

Figure 2.1- Electrical model of the DC motor. 16

Figure 2.2- Electrical model of the PMSM. 17

Figure 2.3 - Oscilloscope screenshot showing the back EMF waveform of a single phase of the Turnigy C80100 130kv BLDC Motor..... 18

Figure 2.4 - Cross section of an Inner Rotor motor (left) and an Outer Rotor motor (right) illustrating the difference in air-gap radius for the same overall diameter. 24

Figure 2.5 - Voltage vector for a three phase PMSM represented in the stator reference frame along with the time varying voltage waveforms..... 27

Figure 2.6 - Voltage vector for a three phase PMSM represented in the alpha-beta reference frame along with the time varying voltage waveforms..... 28

Figure 2.7 - Voltage vector for a three phase PMSM represented in the direct-quadrature reference frame along with the time varying voltage waveforms. 29

Figure 2.8 - Vector diagram for Six-Step Control showing an arbitrary output vector produced in the second state of the six step sequence. 31

Figure 2.9 - Timing diagram showing how the Hall sensor output relates to the phase winding back EMF (Microchip Technology Inc., 2003). 32

Figure 2.10 - Example of a commutation table (Microchip Technology Inc., 2003)..... 32

Figure 2.11 - Three phase H-bridge circuit showing current flow for the PWM on period in red, and the freewheeling current during the PWM off period in green..... 33

Figure 2.12 - Plot of the power dissipated as heat in the semiconductor switch during freewheel current flow through the body diode and the semiconductor switch for the "IRFS7530" transistor. 34

Figure 2.13 - Block diagram of the FOC technique. 36

Figure 2.14 - Vector diagram for SVM showing an arbitrary output vector produced in sector 'S12' of the SVM scheme..... 37

Figure 3.1 - Electric mountain board prototype built as part of final year engineering project. 39

Figure 3.2 - MATLAB Model simulation of the power requirements for the electric longboard as a function of speed and various angles of incline. 47

Figure 3.3 - MATLAB model simulation of the range predictions as a function of speed and various angles of incline.....	48
Figure 3.4 - MATLAB Model simulation for battery current requirement as a function of speed and various angles of incline.	49
Figure 3.5- MATLAB Model simulation for the power loss in each of the two motors as a function of speed and various angles of incline.....	51
Figure 3.6 - MATLAB Model simulation for power loss in the battery pack as a function of speed and various angles of incline.	53
Figure 3.7 - MATLAB Model simulation for power loss in each of the two inverters as a function of speed and various angles of incline.....	54
Figure 3.8 - Cross section of the stock Turnigy SK3 6374-149 PMSM.	55
Figure 3.9 - The longboard truck after machining, extension of the aluminium axle, and location of the inside end bearing mount.	56
Figure 3.10 – Photograph of the modified longboard truck and stator assembly.	57
Figure 3.11 - Cross section of the motor stator showing the positions of the Hall Effect sensors for 120° electrical spacing.....	58
Figure 3.12 - Hall sensor positioned in between stator teeth.	59
Figure 3.13 - Exploded view of the electric longboard hub motor assembly.....	60
Figure 3.14 - Cross section view of the electric longboard hub motor assembly.....	60
Figure 3.15 - Photograph of the actual electric skateboard hub motor assembly viewed from the underside (left) and the top side (right).....	61
Figure 3.16 - Fibreglass enclosure for the electrical components of the electric longboard.	62
Figure 3.17 – Photograph of the complete electric longboard prototype.	62
Figure 4.1 - Snippet from the AUIRFS8409-7P datasheet showing some of the key specifications of the MOSFET that was selected for use in the prototype electric skateboard motor controllers.	64
Figure 4.2 - Gate drive circuit for a single phase of the custom built motor controller.	65
Figure 4.3 - Plot illustrating the relationship between ripple current through the bus capacitors and with varying duty cycle for the electric skateboard motor controller.	67
Figure 4.4 - Plot illustrating the relationship between ripple voltage across the bus capacitors and with varying total bus capacitance for the electric skateboard motor controller.	68
Figure 4.5 - Functional block layout of the Power PCB top side (left) and bottom side (right).....	72
Figure 4.6 - Photograph of the assembled power PCB.	73
Figure 4.7 - Functional block layout of the Control PCB top side (left) and bottom side (right).	73
Figure 4.8 - Photograph of the assembled control PCB top side (left) and bottom side (right).....	74
Figure 4.9 - Photograph of the complete motor controller hardware.	74

Figure 4.10 - Pin-out graphic generated by "STM32CubeMX" software.	78
Figure 4.11 – Clock configuration graphic generated by "STM32CubeMX" software.....	78
Figure 5.1 - Test rig used for the bench testing of the motor controller and the comparison of the two motor control techniques.	84
Figure 5.2 - SolidWorks render of the external Hall sensor mounting assembly in exploded view.	84
Figure 5.3 – Scatter plot showing the electrical power generated as a function of speed for the four different test scenarios.	87
Figure 5.4- Minitab residual plots output for the regression analysis of the combined generator power as a function of speed tests.	88
Figure 5.5 - Graphical representation of the linear line of best fit models for power input under Six-Step Control and FOC, and power generated as a function of motor speed.....	90
Figure 5.6 - Graphical representation of the bench test setup total system efficiency for the driven motor under Six-Step Control and FOC.....	91
Figure 5.7 - Plot showing the difference in total system efficiency for Six-Step Control and FOC as a function of motor speed.....	92
Figure 5.8 - Map showing the route used for the on-road testing.	94
Figure 5.9 - Speed profile for Six-Step Control range and efficiency on-road test number 3 (raw data).	95
Figure 5.10 - Speed profile for FOC range and efficiency on-road test number 3 (raw data).	95
Figure 5.11 – Range and efficiency on-road test 3 speed profiles for both Six-Step Control and FOC with inactive periods removed.....	96
Figure 5.12 - Instantaneous speed measurements for both directions of a single run for Six-Step Control (left) and FOC (right) techniques.	97
Figure 5.13 - Instantaneous speed measurements for three runs return pass only for Six-Step Control (left) and FOC (right) techniques.	97
Figure 5.14 - Instantaneous power measurements for three runs return pass only for Six-Step Control (left) and FOC (right) techniques.	98

List of Tables

Table 1.1 - Legend for Figure 1.1	4
Table 3.1 - Comparison of the advantages and disadvantages of a hub motor setup over a reduction drive setup.....	42
Table 3.2 - Electric longboard motor specifications.	50
Table 3.3 - Electric longboard battery specifications.....	52
Table 3.4 - Electric longboard motor controller specifications.....	54
Table 5.1 - Summary of on-road testing range and efficiency tests for Six-Step Control and FOC techniques.	96
Table 5.2 - Summary of speed and acceleration data from the three speed test runs for Six-Step Control and FOC techniques.....	98
Table 5.3 - Summary of power consumption from the three speed test runs for Six-Step Control and FOC techniques.....	99

Glossary

Term	Definition
Back EMF	The voltage that is generated across a motor's windings as the rotor turns.
Commutation	Switching the electrical current path through a motor's windings in order to achieve continuous rotation.
Copper Loss	Power loss in an electric motor associated with the motor's windings.
Delta (Δ)	Refers to three phase loads where the three phases are terminated in a triangle formation.
Eddy current	Circulating currents within a conductor due to an induced electromotive force.
Electrical angle	The angle of the rotor magnet poles relative to the stator.
H-bridge	A transistor arrangement that allows an output to be connected to the positive DC bus or the negative DC bus.
Integrated Development Environment	Refers to a computer programme suite that provides all the necessary tools and resources for programming and developing software.
Iron Loss	Power loss in an electric motor associated with the iron core of the electromagnets.
Mains supply	A power source from the power supply network. In New Zealand this is 230V, 50Hz single phase AC or 415V, 50Hz three phase AC.
PID Controller	An algorithm which aims to regulate an output based on the difference between a set-point and the measured value of the output (error), the sum of previous errors, and the predicted future error.
Rotor	The rotating component of an electric motor.
Rotor angle	The angle of the rotor relative to the stator.
Remanence	The remaining magnetisation of a ferromagnetic material after an external magnet field has been removed.
Stator	The stationary component of an electric motor.
Windage loss	A term used to represent the energy loss due to the movement of air by a rotating machine.
Wye (Y)	Refers to three phase loads where the three phases are terminated in a wye formation. Also commonly referred to as 'star' terminated loads.

Acronyms

Term	Definition
AC	Alternating Current
ADC	Analogue to Digital Converter
BLDC	Brushless Direct Current
BMS	Battery Management System
CAD	Computer Aided Design
CNC	Computer Numerical Control
DAC	Digital to Analogue Converter
DC	Direct Current
EMF	Electromotive Force
I/O	Input / Output
I2C	Inter-Integrated Circuit
IC	Integrated Circuit
IDE	Integrated Development Environment
LEV	Light Electric Vehicle
LCD	Liquid Crystal Display
MMF	Magnetomotive force
PCB	Printed Circuit Board
PID	Proportional, Integral, Derivative
PM	Permanent Magnet
PMSM	Permanent Magnet Synchronous Motor
PWM	Pulse Width Modulation
RC	Radio Controlled
RPM	Revolutions per minute
SI	Scientific International
SVM	Space Vector Modulation
SWD	Serial Wire Debug
USART	Universal Synchronous Asynchronous Receiver Transmitter

Nomenclature

Symbol	Definition	Units short	Units long
A	Area	m ²	Meters squared
B	Magnetic field	T	Tesla
b	Friction constant	Nm.s/rad	Newton meter seconds per radian
C	Capacity	Ah	Amp hours
C _d	Coefficient of drag	-	-
C _r	Coefficient of rolling resistance	-	-
D	Wheel diameter	m	meters
E	Electric field	N/C	Newtons per coulomb
F	Force	N	Newtons
f	Frequency	Hz	Hertz
H	Magnetic field Strength	A/m	
h	Time	H	Hours
I	Current	A	Amperes
J	Moment of inertia	kg.m ²	Kilogram meters squared
k _m	Per phase motor constant	Nm/A	Newton meters per ampere
K _m	Total motor constant	Nm/A	Newton meters per ampere
K _v	Motor speed constant	V/(rad.s ⁻¹)	Volts per radians per second
K _E	Motor eddy current coefficient	-	-
K _H	Motor core hysteresis coefficient	-	-
l	Length	m	Meters
M	Multiplier for number of active poles	-	-
m	Mass	kg	Kilograms
N	Number of active turns of wire	-	-
P	Power	W	Watts
P _e	Electrical power	W	Watts

P_m	Mechanical power	W	Watts
Q_H	Hysteresis energy loss	J/m ³	Joules per cubic meter
q	Charge	C	Coulombs
R	Resistance	Ω	Ohms
R_m	Reluctance	H ⁻¹	Inverse henry
r	Radius	m	Meters
t	Time	s	Seconds
V	Voltage	V	Volts
v	Velocity	m/s	Meters per second
v_w	Wheel Speed	km/h	Kilometres per hour
ϵ	Electromotive force	V	Volts
η	Efficiency	-	-
η_d	Drive efficiency	-	-
η_m	Motor efficiency	-	-
θ	Angle of incline	rad	Radians
θ_m	Magnet angle	rad	radians
ρ	Density	kg/m ³	Kilograms per meter cubed
ρ_r	Resistivity	Ωm	Ohm meters
τ	Torque	Nm	Newton meters
ω	Angular velocity	rad/s	Radians per second
Φ_B	Magnetic flux	Wb	Weber