

Copyright is owned by the Author of the thesis. Permission is given for a copy to be downloaded by an individual for the purpose of research and private study only. The thesis may not be reproduced elsewhere without the permission of the Author.

**The Design and Construction
of an
Electronically Beam Steered
Phased Array Antenna.**

A Thesis presented in partial fulfilment of the requirements for the degree
of

Master of Science in Physics

at

Massey University
New Zealand

Christopher James Lee
1996

Abstract.

The design and construction of a simple beam steered phased array antenna was undertaken to demonstrate the operational principles behind such devices. The antenna can be used as a receiver or transmitter, however power requirements dictated that the antenna be tested as a receiver. The design is modular to allow for redevelopment without complete reconstruction. The array is made up of the control module, voltage controlled attenuators and a phase shifting unit. The antenna consists of 16 quarter wave monopoles arranged in a 4X4 square array on an aluminium ground plane. Practical considerations lead to a carrier frequency of 200 MHz.

The heart of a phased array antenna is the phase shifting device. This device controls the direction in which the main radiation lobe propagates. Several phase shifting principles were investigated but time did not allow for an exhaustive investigation of every kind of phase shifter. Initially, a relatively new and novel approach was attempted. When this proved to be unachievable a more traditional (but far less elegant) method was used.

During the phase shifting process, the signal necessarily suffers attenuation as well as the designed phase shift, consequently it is necessary to tailor the signal amplitudes of each array element. The required amplitude control is achieved through the use of 16 voltage controlled attenuators.

A computer package is used to control the phase shifter and attenuators. The design of this package depends on only three factors. The first is the interface between the hardware and the computer (via a serial port in this case). The second factor is the type of control signal the phase shifter and attenuators respond to (in this case a dc voltage). The third factor is the range of voltage required for the phase shifter and attenuators so that their full range can be utilised. This is realised through the use of a microprocessor, a "sample and hold" circuit and several D/A converters.

The antenna and computer control package are essentially independent of each other. If an 8 bit digital phase shifter were to be employed later, the hardware could be used to control this with minimal alteration. In this case the advantage of a modular design is apparent. Various parts of the device can be incrementally improved without alteration to the remaining system. Radical change can be accommodated with minimal adjustments.

Acknowledgements.

I wish to thank my supervisor, Assoc. Prof. Neil Pinder, for his advice, encouragement and interest. I would also like to thank Dr. Anthony Burrell for his assistance in chemistry. Thanks also to other staff who gave advice and interest. Finally, I would like to thank my parents and Donna for their help and encouragement. This work was made possible through the financial assistance of the Telecom Users Association of New Zealand.

Contents

ABSTRACT.	II
ACKNOWLEDGEMENTS.	III

Chapter 1 Introduction.

1.1. INTRODUCTION TO PHASED ARRAY ANTENNA.	1
1.2. ELEMENTARY THEORY.	3
1.3. COUPLING BETWEEN ANTENNA ELEMENTS.	4

Chapter 2 Methods of Phase Shifting.

2.1. JINDALEE B PHASED ARRAY ANTENNA.	9
2.2. DIGITAL PHASE SHIFTERS.	9
2.3. PHASE LOCKED LOOP PHASE SHIFTERS.	10
2.4. DISTRIBUTED AMPLIFIER PHASE SHIFTER.	12
2.5. R - C CIRCUIT PHASE SHIFTERS.	14
2.6. WAVE GUIDE PHASE SHIFTER.	16

Chapter 3 The Phase Shifter.

3.1. DESIGN OF A PHASE SHIFTER.	18
3.2. PRODUCING A BST PHASE SHIFTER.	20
3.3. PIN DIODE PHASE SHIFTER.	26

Chapter 4 The Attenuator.

4.1. AMPLITUDE CONTROL.	32
4.2. ATTENUATOR PERFORMANCE.	33

Chapter 5. Control Software.

5.1. INTRODUCTION.	36
5.2. COMPUTER CONTROL PROGRAM.	37
5.3. DATA RECEPTION PROGRAM.	42
5.4. HARDWARE INTERFACE PROGRAM.	43

Chapter 6 Hardware.

6.1. THE DIGITAL BOARD.	48
6.2. THE ANALOG BOARD.	49
6.3. HARDWARE PERFORMANCE.	50

Chapter 7

ANTENNA DESIGN.	51
----------------------	----

Chapter 8

SIGNAL DETECTION.	56
------------------------	----

Chapter 9 Testing Methodology.

9.1. THE TESTING RANGE.	58
9.2. DATA COLLECTION.	59

Chapter 10 Test Results.

10.1. MEASURED RESULTS.	61
10.2. A SIMPLE ARRAY SIMULATION: "THE STANDARD SIMULATION".	65
10.3. UNCOUPLED HALF WAVE DIPOLE SIMULATION.	66
10.4. FULLY COUPLED DIPOLE SIMULATION.	70

Chapter 11 Conclusion.

11.1. CONCLUSION.....	74
11.2. FUTURE WORK.....	74

Appendicies

A.1. MUTUAL COUPLING.....	76
A.2. PRODUCTION OF BST POWDER.....	80
BIBLIOGRAPHY.....	82

Table of Figures and Tables

Figure 1.1.	BSB antenna	2
Figure 1.2.	Two isotropic sources.....	3
Figure 1.3.	Coordinate system	6
Figure 2.1.	Digital Phase Shifter	10
Figure 2.2a.	PLL.....	11
Figure 2.2b.	PLL with variable phase.....	11
Figure 2.2c.	PLL as a modulator.....	12
Figure 2.3a.	Artificial transmission line.....	14
Figure 2.3b.	Distributed amplifier phase shifter.....	14
Figure 2.3c.	Improved distributed amplifier phase shifter.....	14
Figure 2.4a.	Phase shift of an R-C circuit.....	15
Figure 2.4b.	Amplitude variation of an R-C circuit.....	15
Figure 2.5.	Cascaded network.....	16
Figure 2.6.	Wave guide phase shifter.....	17
Figure 3.1a.	Transmission line.....	19
Figure 3.1b.	Artificial transmission line.....	19
Figure 3.2.	ATL phase shifter.....	20
Figure 3.3.	BST production diagram.....	21
Figure 3.4.	Thermocouple calibration.....	22
Figure 3.5.	Hot press Mk. 1.....	23
Figure 3.6.	Sintering temperature.....	24
Figure 3.7.	Hot press Mk. 2.....	25
Figure 3.8.	Sintering temperature.....	25
Figure 3.9.	PIN diode.....	26
Figure 3.10.	Phase shifter Mk. 1.....	27
Figure 3.11.	Antenna geometry.....	27
Figure 3.12.	Phase shifter Mk. 2.....	28
Figure 3.13a.	Predicted phase/amplitude shift for different resistances.....	29
Figure 3.13b.	Predicted phase/amplitude shift for different resistances.....	30
Figure 3.14.	Measured phase shift.....	31
Figure 3.15.	Photograph of the phase shifter.....	31
Figure 4.1.	PIN diode attenuator.....	33
Figure 4.2.	Practical PIN diode attenuator.....	33
Figure 4.3.	Attenuator performance curves.....	34
Figure 4.4.	Reference voltage dependence.....	35
Figure 4.5.	Photograph of the attenuators.....	35
Figure 5.1.	Control system overview	36
Figure 5.2.	Computer program flow chart.....	38
Figure 5.3.	Coordinate system.....	39
Figure 5.4.	Latch.....	44
Figure 6.1.	Control hardware.....	48
Figure 6.2.	D/A converter.....	49
Figure 6.3a.	Typical attenuator curve.....	49
Figure 6.3b.	Phase shift profile.....	50

Figure 6.4a.	D/A converter performance	51
Figure 6.4b.	D/A converter performance	51
Figure 6.5.	Photograph of digital board	52
Figure 6.6.	Photograph of analog board.....	52
Figure 7.1.	Ground plane of antenna	53
Figure 7.2.	Monopole attachment to the ground	54
Figure 7.3.	Photograph of the antenna	54
Figure 7.4.	Photograph of monopole attachment.....	55
Figure 8.1.	AM demodulator.....	56
Figure 8.2.	Signal detection system	57
Figure 8.3.	Photograph of the radio.....	57
Figure 9.1.	The testing range	58
Figure 9.2.	The transmitter	59
Figure 9.3.	The receiving station	60
Figure 9.4.	Receiving station viewed from the transmitter	60
Figure 10.1.	Measured results.....	62
Figure 10.2.	Measured results.....	62
Figure 10.3.	Measured results.....	63
Figure 10.4.	Measured results.....	63
Figure 10.5.	Measured results.....	64
Figure 10.6.	Measured results.....	64
Figure 10.7.	Standard simulation	65
Figure 10.8.	Standard simulation	66
Figure 10.9.	Uncoupled simulation	67
Figure 10.10.	Uncoupled simulation	67
Figure 10.11.	Uncoupled simulation	68
Figure 10.12.	Uncoupled simulation	68
Figure 10.13.	Uncoupled simulation	69
Figure 10.14.	Uncoupled simulation	69
Figure 10.15.	Coupled simulation	70
Figure 10.16.	Coupled simulation	71
Figure 10.17.	Coupled simulation	71
Figure 10.18.	Coupled simulation	72
Figure 10.19.	Coupled simulation	73
Figure 10.20.	Coupled simulation	73
Figure a.1.	Calculating the mutual coupling.....	77
Figure a.2.	Coordinate system	79
Table 5.1.	Binary numbers.....	45
Table 10.1.	Phase measurements	61